

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
3 June 2004 (03.06.2004)

PCT

(10) International Publication Number
WO 2004/047326 A1

(51) International Patent Classification⁷: **H04B 1/707**

Alfredo [IT/IT]; Telecom Italia S.p.A., Via G. Reiss Romoli, 274, I-10148 Torino (IT).

(21) International Application Number:
PCT/EP2002/012813

(74) Agents: **GIANNESI, Pier, Giovanni et al.**; Pirelli S.p.A., Viale Sarca 222, I-20126 Milano (IT).

(22) International Filing Date:
15 November 2002 (15.11.2002)

(81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, OM, PH, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VN, YU, ZA, ZM, ZW.

(25) Filing Language: English

(26) Publication Language: English

(71) Applicants (*for all designated States except US*): **TELECOM ITALIA S.P.A.** [IT/IT]; Piazza degli Affari, 2, I-20123 Milano (IT). **STMICROELECTRONICS S.R.L.** [IT/IT]; Via C. Olivetti, 2, I-20041 Agrate Brianza (MI) (IT).

(84) Designated States (*regional*): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

(72) Inventors; and


(75) Inventors/Applicants (*for US only*): **ETTORRE, Donato** [IT/IT]; Telecom Italia S.p.A., Via G. Reiss Romoli, 274, I-10148 Torino (IT). **GRAZIANO, Maurizio** [IT/IT]; Telecom Italia S.p.A., Via G. Reiss Romoli, 274, I-10148 Torino (IT). **MELIS, Bruno** [IT/IT]; Telecom Italia S.p.A., Via G. Reiss Romoli, 274, I-10148 Torino (IT). **FINOTELLO, Andrea** [IT/IT]; Telecom Italia S.p.A., Via G. Reiss Romoli, 274, I-10148 Torino (IT). **RUSCITTO,**

Published:

— with international search report

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: METHOD AND DEVICE FOR FINE SYNCHRONIZATION OF A DIGITAL TELECOMMUNICATION RECEIVER



(57) Abstract: A method for the synchronization of a digital telecommunication receiver comprises the steps of: - storing a plurality of consecutive samples E-1, E, M, L, L+1 of an incoming spread spectrum signal in a delay line 56; - determining by interpolation between consecutive samples of the incoming spread spectrum signal, by means of a first digitally controlled interpolator 26, an interpolated early sample (e) anticipating an optimal sampling time instant; - determining by interpolation between consecutive samples of the incoming spread spectrum signal, by means of a second digitally controlled interpolator 24, an interpolated middle sample (m) corresponding to the optimal sampling time instant; - determining by interpolation between consecutive samples of the incoming spread spectrum signal, by means of a third digitally controlled interpolator 28, an interpolated late sample (l) delayed with respect to the optimal sampling time instant; - calculating an error signal ξ as the difference between the energy of the symbols computed from the interpolated early sample (e) and the interpolated late (l) sample; - extracting the sign of the error signal ξ - accumulating the sign of the error signal ξ for the generation of control signals S_E, S_M, S_L for controlling the interpolation phases of the digitally controlled interpolators used for determining the interpolated early (e), middle (m) and late (l) samples. The accumulated value has a positive saturation value of +4 and a negative saturation value of -4.

- 1 -

TITLE

Method and device for fine synchronization of a digital telecommunication receiver

DESCRIPTION

Field of the invention

5 The present invention refers to telecommunication systems and in particular to a method for fine synchronization of a digital telecommunication receiver. The invention also relates to a digital receiver for use in a CDMA (Code Division Multiple Access) system.

10 The CDMA access technique currently finds widespread use in third generation mobile communication systems (e.g. UMTS, CDMA2000) thanks to its higher spectrum efficiency with respect to other access techniques.

15 In a CDMA system the data sequence is spread by a pseudo noise code (hereinafter "PN code") having a broader spectrum width. The efficiency of these systems is highly dependent on the capability of the receiver to continuously maintain precise phase synchronization between the received and the locally generated PN code.

 In fact, without a precise phase synchronization between the received and the locally generated code, the performance loss of the receiver is in the order of several dB even for a mismatch of half of the chip period.

20 The phase synchronisation process is usually accomplished in two steps: code acquisition and code tracking. Code acquisition is the initial search process that brings the phase of the locally generated code to within the chip duration ($T_c = 1/F_c$) of the incoming code. Code tracking is the process of achieving and maintaining fine alignment of the chip boundaries between the incoming and locally generated codes.

25 In particular, the present invention is concerned with the code tracking part of the receiving apparatus, which is generally implemented in the form of a Rake receiver.

30 For a digital receiver a key component is the analog-to-digital converter (ADC). In several applications the sampling clock rate cannot in any case be synchronized with the incoming signal. For example, one of these applications is a CDMA base station receiver where the sum of several signals, non-synchronous among each other, are received and digitised with a single analog-to-digital converter. In these cases, the fine

timing synchronisation (i.e. the code tracking) between the received and locally generated PN code of each user must be achieved through digital methods, as it is not possible to modify the sampling clock phase.

Background art

5 The code tracking operations are performed by a Synchronisation Unit. Several types of code tracking loops have been extensively applied in practical applications and the most popular solution is the so-called Early-Late synchronizer.

10 The Synchronisation Unit receives, as input, the baseband signal $y(t)$ from the receiver front-end, oversampled at the frequency $f_s = N \cdot F_C$ and with at least two samples per chip ($N \geq 2$), and feeds a finger of the Rake receiver with one sample per chip (i.e. the optimal sample), as shown in figure 1. Each finger of the Rake receiver requires its own Synchronisation Unit because the values of timing offset of the different multi-path components demodulated by the different fingers of the Rake receiver are usually not the same.

15 The fine timing synchronisation can be achieved by performing some kind of interpolation among the received samples, in order to get the exact value or, at least, to approximate the received signal in correspondence of the optimal sampling instants t_{opt} . This technique is well known and is disclosed for example in F. M. Gardner, "Interpolation in digital modems – Part I: Fundamentals". IEEE Trans. Communications, vol. 41, pp. 502-508, Mar. 1993 or in L. Erup, F. M. Gardner, 20 "Interpolation in digital modems – Part II: Implementation and Performance".

25 The optimal sampling instant $t_{opt}(t)$ varies with time due time variant nature of the wireless channel and corresponds to the instant in which the amplitude of the received signal is maximal and, simultaneously, the Inter-Symbol Interference (ISI) is minimal. By sampling the received signal in correspondence of the optimal sampling time, it is possible to maximise the Signal to Noise Ratio (SNR) and therefore minimise the Bit Error Rate (BER) at the output of the receiver. The optimal sampling time can be observed in the eye diagram as the point of maximum opening, as shown in figure 2.

In the following it is described the principle of a Synchronisation Unit based on the known art. The description is based on the case of a real signal $y(t)$, but the extension to a complex signal $y(t)$ is straightforward.

5 The block diagram of a Synchronisation Unit 1, described in the prior art is shown in figure 3. The considered scheme operates with a feedback loop. A time continuous signal $y(t)$ is received at the input of the Analog to Digital Converter 2. The signal $y(t)$ is a sequence of pulses with period T_c and shaped, for example, by a couple of root raised cosine (RRC) filters

$$y(t) = \sum_{k=0}^{\infty} u_k \cdot h(t - k \cdot T_c)$$

10 where $u_k = \{-1, +1\}$ is the sequence of transmitted chips and $h(t)$ is the impulse response of the equivalent Raised Cosine (RC) filter with the following expression

$$h(t) = \frac{\sin\left(\frac{\pi \cdot t}{T_c}\right)}{\frac{\pi \cdot t}{T_c}} \cdot \frac{\cos\left(\alpha \cdot \frac{\pi \cdot t}{T_c}\right)}{1 - \left(2 \cdot \alpha \cdot \frac{t}{T_c}\right)^2}$$

The unilateral bandwidth of the signal $y(t)$ is equal to

$$B = \frac{(1 + \alpha)}{2 \cdot T_c}$$

15 where α is the roll-off of the RRC shaping filters.

The ADC converter 2 takes samples of $y(t)$ at uniform intervals t_s , which correspond to an ADC sampling frequency of $f_s = 1/t_s$. The sampling of the analog baseband signal can be performed with different sampling rates. However, the Nyquist criterion requires a minimum ADC sampling rate of two times the unilateral signal
20 bandwidth, namely $f_s \geq 2 \cdot B$.

The signal samples $y(n \cdot t_s) = y(n)$ at the output of the ADC converter 2 are provided to the interpolator 4 that computes the interpolated values $y_1(m \cdot t_1) = y_1(m)$ at intervals t_1 . The goal of the interpolator is to increase the time resolution after the ADC

- 4 -

conversion, so that the time spacing t_1 of the samples at the output of the interpolator is smaller than the time spacing t_s of the samples at the output of the ADC. In general we have

$$\frac{t_s}{t_1} = K$$

5 where K is an integer number greater than one.

Being the samples $y(n)$ at the output of the ADC not taken in correspondence of the optimal time instant, the Synchronisation Unit must first estimate the optimal sampling instant \hat{t}_{opt} and then compute or approximate the value of $y(t)$ in correspondence of that instant. The value $y(\hat{t}_{opt})$ is then provided at the output of the

10 Synchronisation Unit for the subsequent signal processing.

The principle of timing synchronisation through digital interpolation is shown in figure 4 for a case of linear interpolation with $K = 4$.

In the example of figure 4 the signal $y(t)$ in correspondence of the optimal sampling instant t_{opt} is approximated with the interpolated value $y_1(m+3)$.

15 The interpolated value $y_1(m+3)$ is calculated as follows: first it is computed the middle point $y_1(m+2)$ between two consecutive samples $y(n)$ and $y(n+1)$ at the output of the ADC

$$y_1(m+2) = \frac{y(n) + y(n+1)}{2}$$

Similarly, the other two interpolated values $y_1(m+1)$ and $y_1(m+3)$ are

20 computed as the average between one ADC sample and the interpolated value $y_1(m+2)$ calculated in the previous step

$$y_1(m+1) = \frac{y(n) + y_1(m+2)}{2} = \frac{3 \cdot y(n) + y(n+1)}{4}$$

$$y_1(m+3) = \frac{y_1(m+2) + y(n+1)}{2} = \frac{y(n) + 3 \cdot y(n+1)}{4}$$

Of course, by using a more complex interpolation scheme (e.g. parabolic, cubic) or

25 increasing the resolution of the interpolator (i.e. increasing K) it is possible to make

more precise the estimate of the received signal in correspondence of the optimal sampling instant.

The synchronization unit of figure 3 also includes other elements that are essential for the synchronization process. A data filter 5 processes the interpolated samples and selects the optimal sample for the subsequent signal processing. The data filter is indicated within the feedback loop, but it can also be placed outside of the loop. Post-placement may be advantageous in terms of complexity when the data filter is more complicate than the interpolator and a relatively high sampling rate is employed for interpolation.

The optimal sampling instant t_{opt} is estimated by a timing error detector block 6 and filtered by a loop filter 7. The goal of the loop filter is to reject the effect of noise that may affect the optimal sampling time estimate. Finally, the loop filter output drives a controller 3, which provides the control signal to the interpolator 4.

Starting from the general structure of a Synchronisation Unit, shown in figure 3, it is possible to analyse its application in the particular case of a digital CDMA receiver.

A known solution for performing the code tracking operations in a CDMA receiver is the so-called Early-Late synchronizer disclosed for example in John G. Proakis, "*Digital Communications*", 3rd edition, Mc Graw-Hill, New York, 1995.

The joint application of the interpolation and the Early-Late concept for the synchronisation of a CDMA receiver can be found in R. De Gaudenzi, M. Luise, "*A Digital Chip Timing Recovery Loop for Band-Limited Direct-Sequence Spread-Spectrum Signals*". IEEE Trans. On Communications, vol. 41, No. 11, Nov. 1993.

An Early-Late synchronizer exploits the symmetry properties of the signal autocorrelation at the output of the receiver-matched filter.

In the following we suppose that the signal at the input of the Early-Late synchronizer is sampled with two samples per chip ($N = 2$). Two subsequent samples at the input of the Early-Late synchronizer are then separated in time by $T_c/2$ (with $T_c = 1/F_c = \text{chip period}$).

In order to introduce a suitable mathematical notation for sequences with different rates, we denote with k the discrete time index related to the chip period so

that $e(k) = e(k \cdot T_c)$. We also denote with SF the spreading factor. The period of the information symbols before the spreading process is equal to $T_s = SF \cdot T_c$ and the discrete time index related to this symbol period is equal to $(k \text{ div } SF)$, where $A \text{ div } B$ is the integer part of the quotient between A and B.

5 Each received chip can be characterised by an early, a middle and a late samples defined as follows:

early sample: is the sample that anticipates the optimal sampling time instant. The early sample is denoted with $e_I(k)$ and $e_Q(k)$ for the in-phase and in-quadrature component respectively;

10 middle sample: is the sample that, in the absence of timing errors, corresponds to the optimal sample or equivalently to the peak of the received impulse $h(t)$. The middle sample is denoted with $m_I(k)$ and $m_Q(k)$ for the in-phase and in-quadrature component respectively;

late sample: is the sample that is delayed with respect to the optimal sampling time instant. The late sample is denoted with $l_I(k)$ and $l_Q(k)$ for the in-phase and in-quadrature component respectively. The late sample of a given chip is also the early sample of the next chip.

The definition of early, middle and late samples is clarified in figure 5 for the in-phase component and in the case of perfect timing synchronisation. From figure 5 it is possible to notice that the middle sample is the one with the higher energy and minimum ISI. Consequently, it has to be provided to the Rake finger for the descrambling and despreading operations.

20 Moreover, from figure 5 it is possible to observe that, if the impulse response of the complete system is symmetrical and the system has achieved a perfect timing synchronisation, then the energies of the early and late samples are identical.

The two conditions of perfect timing synchronisation can be expressed as follows:

$$\text{Perfect timing synchronisation} \Rightarrow \varepsilon_m = m_I^2(k) + m_Q^2(k) = \text{maximum}$$

$$\text{Perfect timing synchronisation} \Rightarrow \varepsilon_e = e_I^2(k) + e_Q^2(k) = \varepsilon_l = l_I^2(k) + l_Q^2(k)$$

where $\varepsilon_e, \varepsilon_m, \varepsilon_l$ are the energies of the early, middle and late samples respectively.

In the presence of noise the identification of the sample with maximum energy is usually difficult. Instead of sampling the signal in correspondence of the peak, the Early-Late synchronizer identifies the optimal sampling instant through the second
 5 condition: the energy of the early and late samples has to be equal or, in other words, the difference between the two energies must be reduced to zero ($\varepsilon_e - \varepsilon_l = 0$). When such condition is fulfilled the sample between early and late (i.e. the middle) is the optimal sample to be provided to the Rake finger.

Taking into account that in a CDMA system the signal to noise ratio on the
 10 channel is very low, the condition $\varepsilon_e - \varepsilon_l = 0$ must be verified on the symbols after the operations of despreading and integration. Averaging over SF samples leads to mean values of the early and late sample energies and reduces the energy fluctuations due to noise and interference from other users.

A simplified block diagram of a prior art Early-Late synchronizer is shown in
 15 figure 6 for the general case of a real PN (Pseudo Noise) code $c_e(k)$. However, the same scheme is valid in case of complex PN code by simply replacing each couple of real multiplication units with one complex multiplication unit.

The Early-Late synchronizer of figure 6 uses two correlators: the first performs the despreading and integrate and dump operations on the early samples while the
 20 second correlator performs the same operations on the late samples. The outputs of the two correlators are then squared in order to get the energy of the despread symbols, to remove the modulation of the data sequence and the phase rotation introduced by the propagation channel. Finally, an error signal ξ is computed by taking the difference of the two-correlator outputs.

25 After the operations of despreading, integration, squaring and sum of the in-phase and in-quadrature components the error signal, for a certain timing error $\tau = t - t_{opt}$, is given by

$$\xi(k \text{ div } SF) = E(k \text{ div } SF) - L(k \text{ div } SF)$$

The characteristic of the Early-Late synchronizer in terms of error signal ξ as a function of the timing error τ is shown in figure 7. The Early-Late characteristic, due to its particular shape, is usually referred to as S-curve.

From figure 7 we observe that when a timing offset is present ($\tau \neq 0$), the error signal ξ at the output of the Early-Late synchronizer is nonzero and the time position of the early, middle and late samples must be delayed or advanced (depending on the sign of the error) to get the optimal sampling instant.

An alternative solution for finely adjusting the time position of the early, middle and late samples, without delaying or advancing their positions, consists in using three digital interpolators as shown, in the particular case of a timing offset $\tau = T_c / 4$, in figures 8 and 9.

Two of these interpolators are used to compute the early E and the late L samples while the third interpolator is used to compute the middle M sample (i.e. the optimal sample with the maximum energy). The early and late samples are provided to the correlators for the computation of the error signal ξ , while the middle sample is provided to the Rake finger for the subsequent signal processing (descrambling, despreading, channel estimation and compensation, decoding, etc.).

If we consider in figure 8 the early E, the middle M and the late L samples, we observe that, by means of a linear interpolator, it is possible to generate, with a certain resolution, all the samples between two subsequent values early E and middle M or middle M and late L. In the case of error signal larger than zero the optimal sampling time is delayed with respect to the middle M sample and therefore the value of the optimal sample can be computed with a linear interpolation between the middle M and the late L samples. In a similar way for an error signal lower than zero, the optimal sample is computed by means of a linear interpolation between the early E and the middle M samples.

In order to compute the delayed or advanced version of the samples early E and late L, determining the error signal, it can be necessary to interpolate the early E sample between the previous sample E-1 and the middle M sample and, in similar way, the late L sample between the subsequent sample L+1 and the middle M sample, as it is possible to observe in figure 9. Therefore a Synchronisation Unit based on the Early-

Late synchronizer requires the knowledge of five subsequent samples E-1, E, M, L, L+1 of the incoming signal spaced of $T_c/2$ among each other.

The three interpolators are used to finely adjust the time position of the early, late and middle samples feeding the correlators and the Rake finger respectively. These
5 interpolators are controlled by a digital signal derived from the error signal ξ of the Early-Late synchronizer. If the loop is correctly designed so to obtain a negative feedback, the system automatically minimizes the error signal by converging towards the error zero condition. The minimum error condition is equivalent to say that the middle sample is the one with the maximum energy and therefore the optimal one.

10 The time position of the three interpolated samples (early, middle and late) is moved backward or forward by a time factor δ when the error signal is respectively positive or negative. The factor δ represents the time resolution of the interpolators and it is usually equal to $T_c/8$.

15 The interpolation of the middle sample with a time-resolution of $\delta = T_c/8$ is usually sufficient to get a negligible degradation of the system performance with respect to an ideal interpolator having infinite resolution. An interpolator having a resolution of $T_c/8$ is however a rather complex circuit, affecting negatively the silicon area requirements on the chip.

20 The early and the late samples feed the correlators that compute the error signal ξ . The time distance Δ between the early and the late samples is defined as *early-late spacing*. The classical implementations of the Early-Late synchronizer employ a fixed early-late spacing, usually equal to the chip period T_c .

25 The Applicant has tackled the problem of reducing the overall complexity and silicon requirement of a synchronization unit in a digital receiver for use in a CDMA system.

30 The Applicant observes that, in a digital receiver, an interpolator having a resolution of $\delta = T_c/8$ is a rather complex circuit, mostly due to the fact that the mathematical operations required to perform a linear interpolation with resolution $\delta = T_c/8$ are complex operations, i.e. sums, divisions by two and multiplications by a constant factor equal to 3. The complexity of the single interpolator affects negatively

the chip area, especially in case of a base station receiver where many of these interpolators are required to process the signals of the various users.

In fact, each Rake finger of a digital receiver needs six interpolators: early, middle and late for both signal components (I and Q). Moreover if we consider, as a possible example, a UMTS base station with 64 different Rake receivers, each with $N_f = 8$ fingers, it is then evident from these numbers that employing interpolators having reduced complexity is a remarkable advantage.

In view of the above, it is an object of the invention to provide a method and a device for fine synchronization of a digital receiver having reduced complexity. Thanks to the reduced complexity, it is possible to reduce the area of the silicon chip in which the system is integrated.

The above and other objects are reached by the method and the device realised according to the invention, as claimed in the accompanying claims.

Summary of the invention

The Applicant has found that, using a variable time distance between the early and late samples, it is possible to remarkably simplify the architecture of the corresponding interpolators. To this end, the interpolation structure of the device provides for a variable early-late spacing, as a function of timing error τ .

The method and the device according to the invention allow simplifying the interpolators of the early and late samples of each rake finger, therefore reducing the complexity of the whole system.

Brief description of the drawings

Figure 1 is a block diagram of a prior art module of a Rake Receiver;

figure 2 is an example of an eye diagram showing an optimal sampling time instant;

figure 3 is a block diagram of a prior art synchronization unit;

figure 4 is a graph showing timing synchronization by means of signal interpolation;

figure 5 is a graph showing early, middle and late samples on a received signal;

figure 6 is a simplified block diagram of an Early-Late synchronizer;

- 11 -

figure 7 is a graph of an error signal in an Early-Late synchronizer;

figures 8 and 9 show a known principle of digital Early-Late synchronizer exploiting the interpolation;

figure 10 is a complete block diagram of a digital Early-Late synchronizer with
5 feedback loop, according to the invention;

figure 11 is a digitally controlled interpolator used in the synchronizer of
figure 10;

figure 12 is a diagram showing the Early-Late spacing as a function of timing
error τ , according to the invention;

10 figure 13 and figure 14 are tables illustrating the mathematical operations
required to perform a linear interpolation according to the invention;

figure 15 is a block diagram of a complete structure of interpolators according to
the invention; and

figure 16 is a table illustrating the values of control signals of the interpolators of
15 figure 15.

Description of preferred embodiments

A device according to the present invention will now be described in detail with
reference to the UMTS (Universal Mobile Telecommunications System) systems, in the
particular case of a UMTS receiver operating in the FDD mode (Frequency Division
20 Duplex).

A complete Early-Late synchronizer 18, which can be used in a digital
communication receiver for maintaining fine alignment between an incoming spread
spectrum signal and a locally generated code, is shown in figure 10.

The device 18 comprises:

25 - a delay line 56 for storing a plurality of consecutive samples $E-1$, E , M , L , $L+1$
of the incoming spread spectrum signal;

- a first digitally controlled interpolator 26 for determining by interpolation
between consecutive samples an interpolated early sample (e) anticipating an optimal
sampling time instant;

- 12 -

- a second digitally controlled interpolator 24 for determining by interpolation between consecutive samples an interpolated middle sample (m) corresponding to the optimal sampling time instant;

5 - a third digitally controlled interpolator 28 for determining by interpolation between consecutive samples an interpolated late sample (l) delayed with respect to said optimal sampling time instant;

10 - a first correlator 32 performing the despreading and integrate and dump operations on the interpolated early sample (e), and a second correlator 30 performing the same operations on the interpolated late sample (l); the outputs of the two correlators are squared in order to get the energy of the despread symbols and to remove the modulation of the data sequence and the phase rotation introduced by the propagation channel; finally, an error signal ξ is computed by taking the difference of the two-correlator outputs;

15 - a low pass filter 22 for averaging the error signal ξ on a certain number of symbols;

 - a circuit 23 for extracting the sign of the error signal ξ ;

20 - a control signal generator 66 for accumulating the sign of the error signal ξ in an internal register, for the generation of control signals S_E , S_M , S_L for controlling the interpolation phases of the first 26, second 24 and third 28 digitally controlled interpolators.

The time distance between the interpolated early (e) and late (l) samples varies in relation with the control signals S_E , S_M , S_L , as will be explained in detail below.

25 The early-late synchronizer 18 is a closed loop control system whose bandwidth is relatively narrow compared to the chip rate F_C . The low pass filter 22, used to average the error signal ξ on a certain number symbols, determines the loop bandwidth. In order to maintain a precise code synchronisation, the loop bandwidth must be large enough to track the instantaneous delay of the correlation function but sufficiently narrow to reject the effects of noise and interference.

The system therefore automatically minimizes the error signal by converging towards the error zero condition. The minimum error condition is equivalent to say that the middle sample is the one with the maximum energy and therefore the optimal one.

Each of the digitally controlled interpolators 24, 26, 28 is a device, as the one shown in figure 11, receiving three input signals, denoted as y_E , y_M , y_L and a control signal denoted with SEL. The output of the interpolator y_{OUT} is a function of the four inputs, $y_{OUT} = f(y_E, y_M, y_L, SEL)$.

The inputs y_E , y_M and y_L are fed with three consecutive samples of the digital signal $y(t)$ to be interpolated (the samples stored in the delay line 56). The time position, or interpolation phase, of the interpolated sample can be selected through the control signal SEL, as will be explained later on in detail.

The middle sample is provided to the Rake finger for the further base-band processing and it has to be selected with sufficient precision in order not to reduce the performance of the receiver in terms of Bit Error Rate (BER).

According to the invention, the time resolution of the first 26 and third 28 digitally controlled interpolators is lower than the time resolution of the second digitally controlled interpolator 24.

In particular, assuming that the consecutive input samples E-1, E, M, L, L+1 are time spaced of $T_C/(2 \cdot n)$, where T_C is the period of an elementary waveform and $n=1, 2, 3, \dots$ is an integer, the time resolution used for determining by interpolation the interpolated early (e) and late (l) samples is $T_C/(4 \cdot n)$, while the time resolution used for determining the middle interpolated sample (m) is $T_C/(8 \cdot n)$.

In the embodiment shown in figure 10, as the input samples are time spaced of $T_C/2$, the early and late interpolators 26, 28 have a time resolution of $T_C/4$, while the middle interpolator 24 has a resolution of $T_C/8$.

Figure 12 illustrates five consecutive received signal samples 56 (E-1, E, M, L, L+1), time spaced of $T_C/2$ on a time axis t , and nine different interpolation patterns corresponding to nine different timing errors τ (from $\tau=-T_C/2$ to $\tau=T_C/2$). The interpolated early samples are shown in figure 12 by square symbols 50, the

interpolated middle samples by diamond symbols 54 and the interpolated late samples by star symbols 52.

As can be seen in figure 12, the early-late spacing Δ is variable and takes the two values T_C or $3 \cdot T_C/4$, alternatively, as a function of timing error τ .

5 In particular the early-late spacing Δ is equal to T_C when timing error τ is zero or an even multiple of $T_C/8$ (corresponding to an even value of control signal S_M):

$$\Delta = T_C \quad \text{when} \quad \tau = \pm 2 \cdot n \cdot \frac{T_C}{8} \quad n = 0, 1, 2, \dots$$

and is equal to $3 \cdot T_C/4$ when timing error τ is an odd multiple of $T_C/8$ (corresponding to a odd value of control signal S_M):

$$10 \quad \Delta = 3 \cdot T_C/4 \quad \text{when} \quad \tau = \pm (2 \cdot n + 1) \cdot \frac{T_C}{8} \quad n = 0, 1, 2, \dots$$

The interpolated middle sample 54, computed with a resolution of $T_C/8$, is always taken as the midpoint between the early 50 and the late 52 samples in order to ensure the error signal balancing.

15 The output values $y_{OUT} = f(y_E, y_M, y_L, SEL)$ of the digitally controlled interpolator 24, having a time resolution of $T_C/8$ are listed in the table of figure 13.

The table of figure 14 illustrates the output values $y_{OUT} = f(y_E, y_M, y_L, SEL)$ of the digitally controlled interpolators 26, 28, having a time resolution $\delta = T_C/4$.

20 As it is shown in figure 14, the mathematical operations required to perform a linear interpolation with resolution $\delta = T_C/4$ are only sums and divisions by two (i.e. right shifts), therefore the hardware complexity of such linear interpolators is much lower than an interpolator with resolution $\delta = T_C/8$.

25 In figure 15 is illustrated the complete structure of the early-middle-late interpolators for one signal component. The structure has been shown for the in-phase component I of the signal, however the same structure is valid also for the in-quadrature Q component.

The block that generates the control signals for the interpolators is shown in figure 10 and figure 15 as block 66.

- 15 -

The control signal generator 66 receives, as input, the sign of the error signal ξ , computed according to the following rule

$$\text{sign}(\xi) = \begin{cases} +1 & \text{if } \xi > 0 \\ 0 & \text{if } \xi = 0 \\ -1 & \text{if } \xi < 0 \end{cases}$$

and provides as output the control signals S_E , S_M and S_L for the three
5 interpolators of the early, middle and late samples respectively. The control signals S_E , S_M and S_L generated by block 66 are the same for both the in-phase and in-quadrature component interpolators.

The control signal S_M for the interpolator 24 working on the middle samples is
10 obtained by accumulating the sign of the error signal, with a saturation for values larger than 4 or smaller than -4, in order to generate a control signal consistent with the table of figure 13. The algorithm employed for the generation of the signal S_M is the following

$$S_M(-1) = 0$$

$$S_M(n) = S_M(n-1) + \text{sign}(\xi)$$

$$\text{if } [S_M(n) > 4] \text{ then } S_M(n) = 4$$

$$\text{if } [S_M(n) < -4] \text{ then } S_M(n) = -4$$

The values of the control signals S_E and S_L for the early and late interpolators
15 respectively, can be derived as a function of the control signal S_M from figure 11 and from the table of figure 14. In particular, the values of the control signals S_E , S_L and S_M as a function of the timing offset τ are given in the table of figure 16.

The expressions of the control signals S_E and S_L can be computed as a function of the signal S_M :

$$20 \quad S_E = \left\lfloor \frac{S_M}{2} \right\rfloor \quad S_L = \left\lfloor \frac{S_M + 1}{2} \right\rfloor$$

where the function $\lfloor \cdot \rfloor$ approximates the argument to the nearest lower integer.

A further reduction of the complexity can be obtained by using a single time multiplexed interpolator for the computation of the interpolated early sample and the

interpolated late sample. The multiplexing is possible because, using a single correlator, the early and the late samples are computed at different time intervals: the early sample is computed during the first half of each DPCCH bit and the late during the second half.

5 The device previously described allows the fine synchronization of a digital telecommunication receiver by means of a method, for maintaining fine alignment between the incoming spread spectrum signal and a locally generated code, comprising the following steps:

- storing a plurality of consecutive samples E-1, E, M, L, L+1 of the incoming spread spectrum signal in a delay line 56;
- 10 - determining by interpolation between consecutive samples of the incoming spread spectrum signal, by means of a first digitally controlled interpolator 26, an interpolated early sample (e) anticipating an optimal sampling time instant;
- determining by interpolation between consecutive samples of the incoming spread spectrum signal, by means of a second digitally controlled interpolator 24, an
15 interpolated middle sample (m) corresponding to the optimal sampling time instant;
- determining by interpolation between consecutive samples of the incoming spread spectrum signal, by means of a third digitally controlled interpolator 28, an interpolated late sample (l) delayed with respect to the optimal sampling time instant;
- 20 - calculating an error signal ξ as the difference between the energy of the symbols computed from the interpolated early sample (e) and the interpolated late (l) sample;
- extracting the sign of the error signal ξ ;
- accumulating the sign of the error signal ξ for the generation of control signals S_E , S_M , S_L for determining the interpolation phases of the digitally controlled
25 interpolators used for computing the interpolated early (e), middle (m) and late (l) samples. The accumulated value has a positive saturation value of +4 and a negative saturation value of -4.

30 The phases, or time position, of the early and late interpolators 26, 28 are controlled by the control signals S_E and S_L in such a way that the time distance between the interpolated early (e) and late (l) samples is made variable, as previously described with reference to figure 12.

In particular, the time distance between the interpolated early (e) and late (l) samples assumes, alternatively, a value of T_c , where T_c is the period of an elementary waveform, when the first control signal (S_M) is an even value, or a value of $3 \cdot T_c/4$ when the first control signal (S_M) is an odd value.

5 Thanks to the variable spacing between the early and the late samples, the time resolution of the respective interpolators 26, 28 can be lower than the time resolution of the interpolator 24 used for determining the middle interpolated sample (m).

10 In the embodiment previously described the time resolution of interpolators 26, 28 is half than the time resolution of interpolator 24, in particular the time resolution of interpolators 26, 28 is $T_c/4$ and the time resolution of interpolator 24 is $T_c/8$.

In general the relation between the time resolution of interpolators is the following, supposing that the samples of the incoming spread spectrum signal are time spaced of $T_c/(2 \cdot n)$, where T_c is the period of an elementary waveform and n is an integer:

- 15
- $T_c/(4 \cdot n)$ is the time resolution of interpolators 26, 28;
 - $T_c/(8 \cdot n)$ is the time resolution of interpolators 24.

The time distance between the interpolated early (e) and late (l) samples assumes, alternatively, a value of T_c or a value of $3 \cdot T_c/4$, depending on the values of control signals S_E and S_L , according to the diagram of figure 12.

CLAIMS

1. A method for fine synchronization of a digital telecommunication receiver, comprising a code tracking process for maintaining fine alignment between an incoming spread spectrum signal and a locally generated code, said method comprising:

- 5 - storing a plurality of consecutive samples (E-1, E, M, L, L+1) of said incoming spread spectrum signal in a delay line (56);
- determining by interpolation between consecutive samples of said incoming spread spectrum signal, by means of a first (26) digitally controlled interpolator, an interpolated early sample (e) anticipating an optimal sampling time instant;
- 10 - determining by interpolation between consecutive samples of said incoming spread spectrum signal, by means of a second (24) digitally controlled interpolator, an interpolated middle sample (m) corresponding to said optimal sampling time instant;
- determining by interpolation between consecutive samples of said incoming spread spectrum signal, by means of a third (28) digitally controlled interpolator, an
- 15 interpolated late sample (l) delayed with respect to said optimal sampling time instant;
- calculating an error signal (ξ) as the difference between the energy of the symbols computed from said interpolated early (e) and late (l) samples;
- characterised in that said method further comprises the following steps:
- extracting the sign of said error signal (ξ);
- 20 - accumulating said sign of said error signal (ξ) for the generation of control signals (S_E , S_M , S_L) for controlling the interpolation phases of said digitally controlled interpolators;
- wherein the time distance between said interpolated early (e) and late (l) samples varies in relation with a first of said control signal (S_M), and the time resolution used for determining by interpolation said interpolated early (e) and late (l) samples is lower than
- 25 the time resolution used for determining by interpolation said middle interpolated sample (m).

2. A method according to claim 1, wherein said step of accumulating said sign of said error signal (ξ) provides that the value accumulated has a positive saturation value of +4 and a negative saturation value of -4.

- 30 3. A method according to claim 1 or 2, wherein the time distance between said interpolated early (e) and late (l) samples assumes, alternatively, a value of T_C , where

T_C is the period of an elementary waveform, when said first control signal (S_M) is an even value, or a value of $3 \cdot T_C/4$ when said first control signal (S_M) is an odd value.

4. A method according to claim 2, wherein a second control signal (S_E), for controlling said first digitally controlled interpolator (26), is generated as a function of said first control signal (S_M), according to the formula:

$$S_E = \left\lfloor \frac{S_M}{2} \right\rfloor$$

where the function $\lfloor \cdot \rfloor$ approximates the argument to the nearest lower integer.

5. A method according to claim 2, wherein a third control signal (S_L), for controlling said third digitally controlled interpolator (28), is generated as a function of said first control signal (S_M), according to the formula:

$$S_L = \left\lfloor \frac{S_M + 1}{2} \right\rfloor$$

where the function $\lfloor \cdot \rfloor$ approximates the argument to the nearest lower integer.

6. A method according to claim 1, wherein the time resolution used for determining by interpolation said interpolated early (e) and late (l) samples is half than the time resolution used for determining by interpolation said middle interpolated sample (m).

7. A method according to claim 6, wherein said plurality of consecutive samples (E-1, E, M, L, L+1) are time spaced of $T_C/(2 \cdot n)$, where T_C is the period of an elementary waveform and n is an integer, the time resolution used for determining by interpolation said interpolated early (e) and late (l) samples is $T_C/(4 \cdot n)$ and the time resolution used for determining by interpolation said middle interpolated sample (m) is $T_C/(8 \cdot n)$.

8. A method according to claim 6, wherein said plurality of consecutive samples (E-1, E, M, L, L+1) are time spaced of $T_C/2$, where T_C is the period of an elementary waveform, the time resolution used for determining by interpolation said interpolated early (e) and late (l) samples is $T_C/4$ and the time resolution used for determining by interpolation said middle interpolated sample (m) is $T_C/8$.

9. A digital communication receiver comprising a device for maintaining fine alignment between an incoming spread spectrum signal and a locally generated code, said device comprising:

- a delay line (56) for storing a plurality of consecutive samples (E-1, E, M, L, L+1) of said incoming spread spectrum signal;

- a first digitally controlled interpolator (26) for determining by interpolation between consecutive samples stored in said delay line (56) an interpolated early sample (e) anticipating an optimal sampling time instant;

- a second digitally controlled interpolator (24) for determining by interpolation between consecutive samples stored in said delay line (56) an interpolated middle sample (m) corresponding to said optimal sampling time instant;

- a third digitally controlled interpolator (28) for determining by interpolation between consecutive samples stored in said delay line (56) an interpolated late sample (l) delayed with respect to said optimal sampling time instant;

- at least a correlator (30, 32, 22) for calculating an error signal (ξ) as the difference between the energy of the symbols computed from said interpolated early (e) and late (l) samples;

characterised in that said device further comprises:

- a circuit (23) for extracting the sign of said error signal (ξ);

- a control signal generator (66) for accumulating said sign of said error signal (ξ) in a register for the generation of control signals (S_E , S_M , S_L) for controlling the interpolation phases of said first (26), second (24) and third (28) digitally controlled interpolators;

wherein the time distance between said interpolated early (e) and late (l) samples varies in relation with a first of said control signals (S_M), and the time resolution of said first (26) and third (28) digitally controlled interpolators is lower than the time resolution of said second (24) digitally controlled interpolator.

10. A digital communication receiver according to claim 9, wherein said register in which is accumulated the sign of said error signal has a positive saturation value of +4 and a negative saturation value of -4.

11. A digital communication receiver according to claim 9 or 10, wherein the time distance between said interpolated early (e) and late (l) samples assumes, alternatively, a value of T_C , where T_C is the period of an elementary waveform, when said first control

signal (S_M) is an even value, or a value of $3 \cdot T_c/4$ when said first control signal (S_M) is an odd value.

12. A digital communication receiver according to claim 10, wherein a second control signal (S_E), for controlling said first digitally controlled interpolator (26), is generated as a function of said first control signal (S_M), according to the formula:

$$S_E = \left\lfloor \frac{S_M}{2} \right\rfloor$$

where the function $\lfloor \cdot \rfloor$ approximates the argument to the nearest lower integer.

13. A digital communication receiver according to claim 10, wherein a third control signal (S_L), for controlling said third digitally controlled interpolator (28), is generated as a function of said first control signal (S_M), according to the formula:

$$S_L = \left\lfloor \frac{S_M + 1}{2} \right\rfloor$$

where the function $\lfloor \cdot \rfloor$ approximates the argument to the nearest lower integer..

14. A digital communication receiver according to claim 9, wherein the time resolution used for determining by interpolation said interpolated early (e) and late (l) samples is half than the time resolution used for determining by interpolation said middle interpolated sample (m).

15. A digital communication receiver according to claim 14, wherein said plurality of consecutive samples (E-1, E, M, L, L+1) are time spaced of $T_c/(2 \cdot n)$, where T_c is the period of an elementary waveform and n is an integer, the time resolution used for determining by interpolation said interpolated early (e) and late (l) samples is $T_c/(4 \cdot n)$ and the time resolution used for determining by interpolation said middle interpolated sample (m) is $T_c/(8 \cdot n)$.

16. A digital communication receiver according to claim 14, wherein said plurality of consecutive samples (E-1, E, M, L, L+1) are time spaced of $T_c/2$, where T_c is the period of an elementary waveform, the time resolution used for determining by interpolation said interpolated early (e) and late (l) samples is $T_c/4$ and the time

resolution used for determining by interpolation said middle interpolated sample (m) is $T_c/8$.

17. A digital communication receiver according to claim 9 or 10, wherein said delay line (56) stores five consecutive samples (E-1, E, M, L, L+1) of said incoming spread spectrum signal.

18. A digital communication receiver according to claim 17, wherein said first digitally controlled interpolator (26), which is controlled by said second (S_E) control signal, receives in input the first three samples (E-1, E, M) stored in said delay line (56), and generates said interpolated early sample (e) as a function of said second control signal (S_E) and said first three samples (E-1, E, M).

19. A digital communication receiver according to claim 17, wherein said second digitally controlled interpolator (24), which is controlled by said first (S_M) control signal, receives in input the three middle samples (E, M, L) stored in said delay line (56) and generates said interpolated middle sample (m) as a function of said first control signal (S_M) and said three middle samples (E, M, L).

20. A digital communication receiver according to claim 17, wherein said third digitally controlled interpolator (28), which is controlled by said third (S_L) control signal, receives in input the last three samples (M, L, L+1) stored in said delay line (56) and generates said interpolated late sample (l) as a function of said third control signal (S_L) and said last three samples (M, L, L+1).

21. A digital communication receiver according to claim 9, wherein said first digitally controlled interpolator (26) and said third digitally controlled interpolator (28) are realized as a single time multiplexed digitally controlled interpolator, the interpolated early (e) and the interpolated late (l) samples being computed at different time intervals.

1/7




Fig. 1




Fig. 2




Fig. 3

2/7




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8

417




Fig. 9




Fig. 10

5/7




Fig. 11




Fig. 12

6/7

SEL	Timing offset (τ)	$y_{OUT} = f(y_E, y_M, y_L, SEL)$
4	$-\frac{T_C}{2}$	$y_{OUT} = y_E$
3	$-\frac{3 \cdot T_C}{8}$	$y_{OUT} = \frac{y_M + 3 \cdot y_E}{4}$
2	$-\frac{T_C}{4}$	$y_{OUT} = \frac{y_M + y_E}{2}$
1	$-\frac{T_C}{8}$	$y_{OUT} = \frac{3 \cdot y_M + y_E}{4}$
0	0	$y_{OUT} = y_M$
-1	$\frac{T_C}{8}$	$y_{OUT} = \frac{y_L + 3 \cdot y_M}{4}$
-2	$\frac{T_C}{4}$	$y_{OUT} = \frac{y_L + y_M}{2}$
-3	$\frac{3 \cdot T_C}{8}$	$y_{OUT} = \frac{3 \cdot y_L + y_M}{4}$
-4	$\frac{T_C}{2}$	$y_{OUT} = y_L$

Fig. 13

SEL	Timing offset (τ)	$y_{OUT} = f(y_E, y_M, y_L, SEL)$
2	$-\frac{T_C}{2}$	$y_{OUT} = y_E$
1	$-\frac{T_C}{4}$	$y_{OUT} = \frac{y_M + y_E}{2}$
0	0	$y_{OUT} = y_M$
-1	$\frac{T_C}{4}$	$y_{OUT} = \frac{y_L + y_M}{2}$
-2	$\frac{T_C}{2}$	$y_{OUT} = y_L$

Fig. 14

7/7




Fig. 15

Timing offset (τ)	S_E	S_M	S_L
$-T_c/2$	2	4	-2
$-3 \cdot T_c/8$	1	3	2
$-T_c/4$	1	2	1
$-T_c/8$	0	1	1
0	0	0	0
$+T_c/8$	-1	-1	0
$+T_c/4$	-1	-2	-1
$+3 \cdot T_c/8$	-2	-3	-1
$+T_c/2$	-2	-4	-2

Fig. 16

INTERNATIONAL SEARCH REPORT

International Application No

PCT/EP 02/12813

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H04B1/707

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the International search (name of data base and, where practical, search terms used)

EPO-Internal

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 5 493 588 A (LENNEN GARY R) 20 February 1996 (1996-02-20) abstract; figures 3A,3B column 7, line 64 -column 9, line 57	1-21
A	EP 0 932 263 A (NOKIA MOBILE PHONES LTD) 28 July 1999 (1999-07-28) abstract; figures 1,4 page 6, line 49 -page 7, line 28	1-21
A	US 6 201 828 B1 (KOTOV ANATOLI V ET AL) 13 March 2001 (2001-03-13) abstract; figures 2-4 column 4, line 12 - line 64	1-21
	-/--	

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

A document defining the general state of the art which is not considered to be of particular relevance

E earlier document but published on or after the international filing date

L document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

O document referring to an oral disclosure, use, exhibition or other means

P document published prior to the international filing date but later than the priority date claimed

T later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

Z document member of the same patent family

Date of the actual completion of the international search

23 June 2003

Date of mailing of the international search report

01/07/2003

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Ricciardi, M

INTERNATIONAL SEARCH REPORT

International Application No

PCT/EP 02/12813

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP 0 880 238 A (MITSUBISHI ELECTRIC CORP) 25 November 1998 (1998-11-25) abstract; figures 1A-1D, 8 page 17, line 21 -page 18, line 22 -----	1-21
A	US 5 781 152 A (FOUILLAND BERNARD ET AL) 14 July 1998 (1998-07-14) abstract; figures 6-8 column 6, line 47 - line 53 column 10, line 65 -column 11, line 51 -----	1-21

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/EP 02/12813

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 5493588	A	20-02-1996	US 5402450 A US 5854815 A US 5815539 A	28-03-1995 29-12-1998 29-09-1998
EP 0932263	A	28-07-1999	US 6269075 B1 EP 0932263 A2 JP 11261528 A	31-07-2001 28-07-1999 24-09-1999
US 6201828	B1	13-03-2001	AU 759560 B2 AU 5932799 A	17-04-2003 18-05-2000
EP 0880238	A	25-11-1998	JP 11041141 A CA 2237469 A1 CN 1205585 A ,B EP 0880238 A2 US 6154487 A	12-02-1999 21-11-1998 20-01-1999 25-11-1998 28-11-2000
US 5781152	A	14-07-1998	FR 2742612 A1 CA 2192751 A1 CN 1157416 A DE 69616950 D1 DE 69616950 T2 EP 0779518 A1 ES 2167527 T3 RU 2178953 C2	20-06-1997 16-06-1997 20-08-1997 20-12-2001 04-07-2002 18-06-1997 16-05-2002 27-01-2002

INTERNATIONAL SEARCH REPORT

Rec'd PCT/TO 16 MAY 2005

International Application No

PCT/EP 02/12813

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H04B1/707

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 5 493 588 A (LENNEN GARY R) 20 February 1996 (1996-02-20) abstract; figures 3A,3B column 7, line 64 -column 9, line 57	1-21
A	EP 0 932 263 A (NOKIA MOBILE PHONES LTD) 28 July 1999 (1999-07-28) abstract; figures 1,4 page 6, line 49 -page 7, line 28	1-21
A	US 6 201 828 B1 (KOTOV ANATOLI V ET AL) 13 March 2001 (2001-03-13) abstract; figures 2-4 column 4, line 12 - line 64	1-21
-/-		

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *S* document member of the same patent family

Date of the actual completion of the international search	Date of mailing of the international search report
23 June 2003	01/07/2003
Name and mailing address of the ISA European Patent Office, P.B. 5818 Patentlaan 2 NL - 2280 HV Rijswijk Tel. (+31-70) 340-2040, Tx. 31 651 epo nl, Fax: (+31-70) 340-3016	Authorized officer Ricciardi, M

BEST AVAILABLE COPY

INTERNATIONAL SEARCH REPORT

International Application No

PCT/EP 02/12813

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP 0 880 238 A (MITSUBISHI ELECTRIC CORP) 25 November 1998 (1998-11-25) abstract; figures 1A-1D, 8 page 17, line 21 -page 18, line 22	1-21
A	US 5 781 152 A (FOUILLAND BERNARD ET AL) 14 July 1998 (1998-07-14) abstract; figures 6-8 column 6, line 47 - line 53 column 10, line 65 -column 11, line 51	1-21

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/EP 02/12813

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 5493588	A	20-02-1996	US 5402450 A	28-03-1995
			US 5854815 A	29-12-1998
			US 5815539 A	29-09-1998
EP 0932263	A	28-07-1999	US 6269075 B1	31-07-2001
			EP 0932263 A2	28-07-1999
			JP 11261528 A	24-09-1999
US 6201828	B1	13-03-2001	AU 759560 B2	17-04-2003
			AU 5932799 A	18-05-2000
EP 0880238	A	25-11-1998	JP 11041141 A	12-02-1999
			CA 2237469 A1	21-11-1998
			CN 1205585 A ,B	20-01-1999
			EP 0880238 A2	25-11-1998
			US 6154487 A	28-11-2000
US 5781152	A	14-07-1998	FR 2742612 A1	20-06-1997
			CA 2192751 A1	16-06-1997
			CN 1157416 A	20-08-1997
			DE 69616950 D1	20-12-2001
			DE 69616950 T2	04-07-2002
			EP 0779518 A1	18-06-1997
			ES 2167527 T3	16-05-2002
			RU 2178953 C2	27-01-2002